

- Turn on the radio while pressing "PTT" and number "1" on the numeric keyboard
- When "D868UV TEST MODE" appears on the display, release "PTT" and number "1"

In the lower part of the display, it is shown: "430-440 144-146 MODE 00003"

- Change the frequency range using the channel knob.

"Mode 00000" is for the full band

- Turn off the radio to save the changes

Attention:

It is important to do this procedure only BEFORE programming the transceiver.

When opening the CPS, firstly read the radio. Then set up your codeplug. Then write it to the radio.

I suggest you to try to program only one channel for both bands out of the frequency range, to test if the procedure is working, before programming the whole codeplug.

Einstellungen vorher sichern !

"0 ist die Variante mit dem größten Frequenzbereich"

- Wichtig ist halt nur - der Aktuell aufgespielte Codeplug wird gelöscht! Somit Codeplug vorher sichern
- erweitern und Codeplug wieder einspielen - Steht zwar alles dort beschrieben
- aber wer der Englischen Sprache nicht so mächtig ist.....